

INTERSYS CLIENT USER'S QUICK GUIDE



NUVICO®
VALUE SECURED™

CONTENTS

- Contents..... 2**
- Introduction 3**
 - Technical support3
 - Starting Spotter3
- Spotter Basics 4**
 - Viewing Camera Feeds5
 - Viewing Playback Video6
 - Exporting Data.....7
 - Layouts and Settings9
 - PTZ (Dome) Control.....10
 - Camera Tours 12
 - Audio & I/O 13
 - Alarms..... 14
- Spotter Advanced Tips.....15**
 - Zoom 15
 - Virtual Cameras 15
 - Plugin Management 16
 - Autocrop 17
 - VCA Visualization 18
 - Auto-Zoom..... 18
 - Joystick Control..... 19
 - Manual Device Numbering 19
 - Keyboard Shortcuts 20
 - Alarms..... 20
- Copyrights..... 29**

INTRODUCTION

Intersys Client is an easy-to-use light weight application for viewing and exporting real-time and playback video. Intersys Client can be used to create multi-screen solutions with multiple independently operating device tabs and windows. Intersys Client supports camera (analog and digital, including PTZ), audio, and I/O feeds.

TECHNICAL SUPPORT

For technical support, please contact the supplier of the system.

STARTING INTERSYS CLIENT

To log into Intersys Client :


Open the Intersys Client application through the Start menu.

The login screen is displayed. Select the master server, and type your user name and password in the corresponding boxes. Click **Login**.

You can add, remove, and edit master server addresses through the +, -, and 'Edit' buttons.

INTERSYS CLIENT BASICS


After logging in, Intersys Client opens in real-time view mode:



- A) Profile Selection
- B) Device List
- C) Tabs
- D) Work Area

- E) Date & Time
- F) Playback Buttons
- G) Time Bar
- H) Layout Tools

VIEWING CAMERA FEEDS



Viewing real-time video feed from one or multiple cameras:

In the device list, double-click on the name of a camera or drag the camera to the work area.

You can have up to 16 cameras (depending on the license) open simultaneously. You can change the order of the opened cameras by dragging them on the work screen.

Note: Real-time video feeds have **white** borders, while playback video feeds have **green** borders.



Viewing a maximized video feed from one or multiple cameras:

If you want to maximize a camera feed from a single camera, double-click on the image feed from a single camera.

If you want to maximize a camera tab, click the 'Maximize' button next to the name of the tab.


You can return to default view by pressing 'ESC'.

VIEWING PLAYBACK VIDEO



After opening cameras in real-time view as instructed above, you can enter playback mode via multiple ways as instructed below.

Note: Real-time video feeds have **white** borders, while playback video feeds have **green** borders.



Playback via calendar:

In the 'Time Panel', select the date and time by clicking the 'Date' and 'Time' tabs, or select a recent activity by clicking the 'Activity' tab.

Note: The 'Activity' tab contains only activities from the currently opened cameras.



Playback via quick buttons:

Click the quick buttons to play, rewind, and fast forward through the material.


Note: You can always return to the current time by clicking the green play arrow.



Playback via time slider:

You can use the time slider to quickly slide through the material.


Playback via the Time Bar:



You can click on the bottom bar to open the ‘Time Bar’ slider, in which you can slide the marker to the desired playback point.

Note: You can use the mouse wheel on top of the ‘Time Bar’ to adjust the time scale displayed in the time bar. You can also use the ‘Zoom’ slider on the right side of the ‘Time Bar’ to adjust the scale.

EXPORTING DATA




Exporting still images:

You can export still images from a specific camera by moving the mouse over a camera feed and clicking the ‘Export’ button on top of the video feed.

When the export dialogue opens, you can type the location and name of the file, select the desired file format, and select whether to show the date and camera name on the image.

Note: If the options dialogue has been disabled, you can change the options in image export settings as instructed below.





Exporting video clips:


You can export video clips from one or multiple cameras clicking the 'Export' button on the left of the 'Time Bar' at the bottom of the screen. If the 'Time Bar' is not visible, you can open it by clicking on the bottom bar at the bottom of the screen.



After clicking the 'Export' button, select the cameras from which data will be exported. Only cameras that have been opened in the work area can be selected.



After selecting the cameras, choose the start and end points for the clip from the 'Time Bar'. You can center the bar to the start point or the end point by clicking the 'Start' or 'End' buttons, or center between the points by clicking the 'Duration' button.



After selecting the time period, click 'Start Export'. When the export dialogue opens, you can type the location and name of the file, and select the desired file format.

Note: If the options dialogue has been disabled, you can change the options in image export settings as instructed below.

LAYOUTS AND SETTINGS




Using tabs:

By default, cameras are opened to the 'Cameras' tab. You can have multiple camera tabs, each containing a different set of cameras.

To open a new tab, click the + button next to the tab list.


To rename a camera tab, right click on the name of the tab and select 'Rename current tab header'.



Settings:


You can open the settings window by clicking 'Menu' near the upper left corner of the application window.

The 'Settings' window can be used to set the language, password, video and still image export default options, and advanced parameters.



Multiple windows:

You can open multiple simultaneous Intersys Client windows by clicking the 'New Window' button under the device tree, or by dragging a camera or camera tab off from the Intersys Client main window.



Managing layouts:


You can manage layouts by clicking the 'Layouts' button on the bottom right corner of the window.

Layouts contain all information about the current settings, including camera order, tabs, windows, and playback positions.

Layouts can be shared with other users, and you can use layouts they have shared.


Note: You can scale the layout size by using the layout slider next to the 'Layouts' button.

PTZ (DOME) CONTROL




For dome (PTZ) cameras, you can open the dome controls by selecting the camera view and clicking 'Camera' on the toolbar.

You can control the camera by dragging with mouse or with arrow keys.




To zoom, open the dome controls for the camera and either use the mouse scroll button or click 'Zoom' and select the zoom distance.




To view, edit, create, and delete preset positions, click 'Go to' and select the preset position you want to view, or 'Edit preset positions' to edit, delete, or create positions.

Note: You cannot create two preset positions for a single location. If you are unable to create a new position, Spotter has determined a double position and you need to move the camera before creating a new position.



To view, edit, create, and delete tours, click 'Tours' and use the pull-down menu to select the tour you want to view or edit, or 'New' or 'Delete' to create or delete tours.

Note: Creating tours requires preset positions to have been set before they are added to the tours.



To set a PTZ camera's home position, click 'Settings' and 'Edit home position'.

CAMERA TOURS




Camera tour controls are located to the right of the video control buttons. To create a camera tour:

- 1) On the work area, open the cameras you want to add to the tour in the order you want them shown in the tour.
- 2) Click the gear button. The tab name is used as name of the tour. Remember to ensure that “In use” is marked.
- 3) Select “Show cameras one by one” to display one camera at a time, or “show cameras simultaneously” to show one tab of cameras at a time. Check “Run camera tour in maximized window state” to use full screen mod with the camera tour.
- 4) Click the tour ‘Play’ button to start the tour.

You can move between tour cameras or tabs with the ‘Previous’ and ‘Next’ buttons.



AUDIO & I/O




Audio and I/O channels are located on the device tree along with other devices such as cameras.

You can open audio and I/O devices by double clicking on them, causing them to be opened on the *right* side of the work area.

You can change an I/O device state by clicking the small icon on left of the name of the I/O device. You can double click on the name of the I/O device to open a control panel on which you can change the state, or set a change state pulse and define its duration.

ALARMS



You can open the alarm view by clicking the **Alarms** button on the menu, or the alarm switch, which is located on the upper right corner of the screen. In the minimized mode, the alarm switch pulses with a red warning signal if there are active alarms. You can maximize the alarm area by clicking the alarm switch.



After maximizing the alarm area, alarms are displayed as a list that includes the alarm names and the time that lapsed after the alarm was active.

You can open an alarm view on the work area by double clicking an alarm's name on the alarm list.


Alarms are configured and assigned to user profiles in the *System Manager* application. Please see *The Administrator Guide* for further details on alarm creation.

INTERSYS CLIENT ADVANCED TIPS

Zoom

You can zoom in any camera image by holding the right mouse button and using the mouse scroll wheel. When you release the right button, the image resets to its original state.

VIRTUAL CAMERAS




You can easily duplicate an existing camera view for a single camera and create a virtual camera view by selecting 'Camera' -> 'Duplicate'.



After duplicating a camera view, select 'View' -> 'Move / Zoom'.

Select the area you want the virtual camera view to encompass from the camera view, and click 'Ok'.

After the virtual camera has been created, you can move around the whole camera view by holding the right mouse button and using the mouse scroll wheel. When you release the right button, the image resets to its original state.




You can take multiple virtual views of a single camera by duplicating the camera and doing a new 'Move / Zoom' operation on the image.

Similarly, you can move selected virtual areas by clicking 'Move / Zoom' and dragging the selected virtual view.


Note: When zooming the virtual view, the default aspect ratio will be the same as in the original image. If you want to change the aspect ratio, hold 'Shift' while setting the virtual camera boundaries.

PLUGIN MANAGEMENT




All plugins – such as ANPR+ (Automatic Number Plate Recognition) can be managed by clicking 'Plugins' next to 'Menu' on the upper left side of the screen.

AUTOCROP




In some cases, using cameras with varying aspect ratios can cause the work area to feel cluttered and leads to an unaesthetic and distracting use experience.

You can correct the situation by switching on automatic image cropping, which render all camera views the same size.




Automatic image cropping performs this by cropping edge areas from cameras to ensure compatible view sizes. The cropping is purely virtual and does not affect recording or camera feed information.

You can switch on automatic image cropping by right clicking on the tab's name and selecting the option.




VCA VISUALIZATION



If VCA functionality has been enabled for the camera, you can activate VCA visualization from the 'Highlight' menu, by selecting either 'Show tracks' (displays movement routes) or 'Highlight moving objects' (draws a rectangle around each moving target).

You can re-click on the selection to disable the selected VCA visualizations on Intersys Client .

AUTO-ZOOM




If you have a compatible VCA license, you can set the motion detection to auto-zoom around moving objects. Auto-zoom will always attempt to simultaneously zoom on all moving objects within the visible image.

The auto-zoom function will follow the moving objects within the camera view depending on the setting:

On 'Follow motion on whole image area', movement will be followed and zoomed on in the whole image area of the camera (not only the virtual camera area),

On 'Follow motion on the zoomed area', movement will be followed and zoomed within the boundaries of the virtual camera image.

JOYSTICK CONTROL



You can use any DirectX compatible joystick as a control device. A joystick can be fully configured, and each button can be assigned a customizable function.


Configuring a joystick:

Before a joystick can be taken into use, it needs to be configured, first in Windows, then in Intersys Client .

To calibrate a joystick in Windows, open the Control Panel and find ‘Set up USB game controllers under devices and printers. Follow the instructions on calibrating the joystick.

After calibration, start Intersys Client and find ‘Input devices’ on the lower edge of the screen. Select ‘Edit input device settings’, select the device you want to configure in the list, and click ‘Add’. Configure the joystick controls.

MANUAL DEVICE NUMBERING



You can set new shortcut numbers for cameras by clicking ‘Device numbering’ on the menu and de-selecting ‘Use automatic camera numbering’.

You can use the manually configured keyboard shortcuts anywhere in Intersys Client by using the numeric keypad (note: the number row on top of the alphabetic keys cannot be used to open devices).

KEYBOARD SHORTCUTS

You can activate all devices and access most of the functions in Intersys Client with keyboard shortcuts. (When accessing devices, use the numeric keypad; the number row on top of the alphabetic keys cannot be used to open devices).

WINDOWS

Shortcut	Description
Ctrl+N	New window
Alt+F4	Close current window

ALARMS

Shortcut	Description
F5	focuses to first alarm
Enter	Opens the alarm in alarm view tab
Space	acknowledges the focused alarm

DIALOGS

Shortcut	Description
Enter	Same as clicking OK-button in a dialog. If focus is on other button when Enter key is pressed, then the other button's action is executed instead.
Esc	Same as clicking Cancel-button in a dialog (or closing the dialog).

SHOW / HIDE COMPONENTS

Shortcut	Description
F1	Show About window
F2	Reset layout: Set main window to normal state (not maximized). 100% zoom. Show profile window, time panel and time slider. Close export panel in time slider. Focus is not in any component.
F3	Show settings window
Ctrl + F3	Show control device settings window
Shift + F3	Show number mappings settings window
Ctrl+F5	Show / hide alarm window
Ctrl+F6	Show / hide profile window
Ctrl+F8	Show / hide time panel
Ctrl+F9	Minimize / restore tab component panel (if it is open)
Shift+F9	Close tab component panel (if it is open)
Ctrl+F10	Show / hide ribbon (menu items)

When a component is displayed, focus is set to the first item in the component (same functionality as with the shortcut key without Ctrl).

MOVING FOCUS

Shortcut	Description
Tab	Move focus to next element within container component
Shift+Tab	Move focus to previous element within container component
F5	Move focus to first active alarm in alarm list. If no active alarm, move focus to first alarm in list. If alarm window is hidden, show it first

F6	Move focus to first item in profile tree. If profile window is hidden, show it first
F7	Move focus to first camera in current tab
F8	Move focus to time panel. If time panel is collapsed, open it first
F9	Move focus to tab component panel
F10	Move focus to first ribbon menu item. If ribbon is closed, open it first

FULL SCREEN WINDOW

The following shortcuts work in full screen window.

Shortcut	Description
F2	Reset layout
F8	Move focus to time panel
Ctrl+F8	Show /hide time panel
Tab	Move focus to next control (next camera in tab)
Shift+Tab	Move focus to previous control (previous camera in tab)
Ctrl+P	Print video image
Ctrl+S	Save video image
Ctrl+Shift+D	Duplicate video view
Ctrl+Tab	Select next tab. If currently selected tab is last tab, select first tab in the window. Addition (+) tab is not selected.
Ctrl+Shift+Tab	Select previous tab. If currently selected tab is first tab, select last tab in the window. Addition (+) tab is not selected.
Ctrl+T	Create new camera tab. When new camera is created, move focus to first item in device tree (to make it easier to add new cameras).

Ctrl+Shift+W	Close current tab
Esc	Restore from full screen to normal state
Ctrl+D	Date selection
Ctrl+G	Time selection
Ctrl+E	Activity selection
Ctrl+Right	Set playback time +30 seconds
Ctrl+Left	Set playback time -30 seconds
Ctrl+Shift+Right	Set playback time +5 minutes
Ctrl+Shift+Left	Set playback time -5 minutes
Ctrl+Alt+Shift+Left	Set playback time -1 hour
Ctrl+Alt+Shift+Right	Set playback time +1 hour
Ctrl+Shif+Y	Set playback time +1 day
Ctrl+Y	Set playback time -1 day
Ctrl+Enter	Set to current time
Ctrl+Space	Pause playback
Shift+Left	Decrease playback speed
Shift+Right	Increase playback speed
Ctrl+o...Ctrl+9	Camera selection
Ctrl+W	Close selected camera
Alt+Enter	Maximize selected camera

TABS

Shortcut	Description
Ctrl+Tab	Select next tab. If currently selected tab is last tab, select first tab in the window. Addition (+) tab is not selected.
Ctrl+Shift+Tab	Select previous tab. If currently selected tab is first tab, select last tab in the window. Addition (+) tab is not selected.
Ctrl+T	Create new camera tab. When new camera is created, move focus to first item in device tree (to make it easier to add new cameras).
Ctrl+Shift+T	Open tab menu
Ctrl+Shift+W	Close current tab
Alt+Shift+Enter	Maximize current tab to full screen size
Esc	Restore maximized tab to normal size (when no camera is selected)
Ctrl+Shift+C	Automatic image cropping on / off
Ctrl+Shift+R	Reset all camera zooms to full zoom
Ctrl+Shift+B	Bounding box on / off
Ctrl+Shift+A	Tail on / off

PROFILE WINDOW

Shortcut	Description
Enter (when a camera is selected)	Add camera to tab
Enter (when a folder is selected)	Add all cameras in the selected tab and Expand the folder
Left (when selected folder is expanded)	Close the folder

Left (when selected node is not expanded)	Select parent folder
Right (when selected folder is not expanded)	Open the folder
Up and Down	Move selection up or down. When a camera is active, the buttons for that camera are shown in the tab (that camera becomes selected)

PLAYBACK TIME AND SPEED

Shortcut	Description
Ctrl+D	Open date selection panel. Select date with arrow keys and accept selection with Enter. Both Enter and Esc closes date selection panel.
Ctrl+G	Open time selection panel. Select time with arrow keys and accept selection with Enter. When pressing a button, the panel stays open. Esc closes time selection panel.
Ctrl+Right	Set playback time +30 seconds
Ctrl+Left	Set playback time -30 seconds. If in realtime mode, switch to playback mode first, and set 1x speed.
Ctrl+Shift+Right	Set playback time +5 minutes
Ctrl+Shift+Left	Set playback time -5 minutes. If in realtime mode, switch to playback mode first, and set 1x speed.
Ctrl+Alt+Shift+Left	Set playback time -1 hour
Ctrl+Alt+Shift+Right	Set playback time +1 hour
Ctrl+Shif+Y	Set playback time +1 day
Ctrl+Y	Set playback time -1 day
Ctrl+Enter	Go to realtime mode. No action if already in realtime mode.

Ctrl+Space	Pause / play
Shift+Right	Increase playback/fast forward speed. No action in realtime mode.
Shift+Left	Decrease playback/fast forward speed (when speed = 0, start play back/fast rewind). If in realtime mode, switch to playback mode and start playback at 0.5x speed.
Ctrl+Alt+Right	Display next video frame in playback mode
Ctrl+Alt+Left	Display previous video frame in playback mode

Misc

Shortcut	Description
Ctrl+E	Open activity list. Use arrow keys + Enter to select activity. Esc closes activity list without selecting activity. Tab closes menu and sets focus to next element.
Ctrl+L	Open layout menu (layout name selection can be changed with arrow keys, Esc closes menu without selecting layout)
Ctrl+Up	Load previous layout (same order as in layout menu)
Ctrl+Down	Load next layout (same order as in layout menu)

CAMERA SELECTION IN A TAB

Shortcut	Description
Ctrl+1 to Ctrl+0	Set focus to n:th camera in tab (0=10th)
Tab	Next camera
Shift+Tab	Previous camera
Esc	Remove camera selection

CAMERA CONTROLS

Shortcut	Description
Ctrl+W	Close current camera
Alt+Enter	Maximize camera in tab.
Double enter	Maximize / minimize camera in tab
Esc	Restore camera normal size (when maximized). When in normal size, remove focus.
Ctrl+P	Print camera image.
Ctrl+S	Save (export) camera image.
Ctrl+Shift+D	Duplicate video view

DOME CAMERA CONTROL

Shortcut	Description
Arrow buttons	Moving the camera left, right, up, down (also intermediate directions)
Page up	Zoom out
Page down	Zoom in
Home	Full unzoom
End	Maximum zoom in

I/O CONTROL

Shortcut	Description
Arrow buttons	Change focus between action button, content popup button and close button when focus in component panel
Space	Performs default action when item is selected from the profile tree

COPYRIGHTS

© 2014. All rights reserved.

No part of this document may be reproduced for any purpose, even in part, without an explicit permission.

TRADEMARKS

Microsoft and Windows are either trademarks or registered trademarks of Microsoft Corporation in the United States and/or other countries.

Other product and company names may be the registered trademarks of their owners.

COPYRIGHT

Portions of this software are copyrighted by others, as follows:

DirectSkin OCX

WindowBlinds: DirectSkin™ OCX © Stardock®

log4net

Copyright © The Apache Software Foundation

MD5

Copyright © RSA Data Security, Inc. Created 1991. All rights reserved. License to copy and use this software is granted provided that it is identified as the "RSA Data Security, Inc. MD5 Message-Digest Algorithm" in all material mentioning or referencing this software or this function.

License is also granted to make and use derivative works provided that such works are identified as "derived from the RSA Data Security, Inc. MD5 Message-Digest Algorithm" in all material mentioning or referencing the derived work.

RSA Data Security, Inc. makes no representations concerning either the merchantability of this software or the suitability of this software for any particular purpose. It is provided "as is" without express or implied warranty of any kind.

These notices must be retained in any copies of any part of this documentation and/or software.

Windows Media Format Components

This product includes technology owned by Microsoft Corporation and under a license from Microsoft Licensing, GP. Use or distribution of such technology outside of this product is prohibited without a license from Microsoft Corporation and/or Microsoft Licensing, GP as applicable.

Xerces

This product includes software developed by the Apache Software Foundation (<http://www.apache.org/>). Copyright © 1999 The Apache Software Foundation. All rights reserved.