# Quick Setup Guide

## **QUICK SETUP GUIDE**

This document is intended for initial setup only.

The user should read the entire instructions manual before using this product. The user instructions manual can be downloaded via NUVICO's website at:

www.nuvico.com

To start the setup process, connect a USB mouse to any available USB port and right-click on your mouse.

## 1. PASSWORD



Account: **admin**Password: **000000**(6 zero).

#### 2. Main Menu





Once the password has been entered correctly, [Main Menu] will be displayed. Click on the [Setup Menu] icon.

# 3. NETWORK SETUP



# SETUP ▶ NETWOK

The network menu allows for adjustment to network settings for viewing video across a local area network or the Internet.

## CONFIG

The DHCP option can be used to obtain an IP address from a router. Turn this option on at initial set up and save. Once the DVR obtains an IP address from the router, turn the Static IP option on, which maintains the IP addresses obtained from the router. If the network is not configured for the DHCP option, please configure this menu manually. Assistance from an IT technician may be required.

# IP ADDRES, NETMASK, & GATEWAY

Input the appropriate IP ADDRESS, NETMASK, & Default GATEWAY value.

# PRI. & SEC. DNS SERVER

Input the appropriate PRI. DNS SERVER & SEC. DNS SERVER value.

Note: If you are using a dynamic IP internet service, a 'hostname' can be used to connect to the unit. The hostname can be found at the 'System Info' in the Main menu.

i.e., INTERNET EXPLORER: http://hostname.dvrhost.com:port# (For example: http://G123456.dvrhost.com:7000)

# 4. DATE & TIME




## SETUP ▶SYSTEM Menu

Set the "DATE" & "TIME" to the appropriate date and time. Once correctly entered, click the SAVE button to save and exit. (24 hour format)

NOTE: Please stop recording and set NTP SYNC off before setting up the Date & Time.

# 5. RECORD



### SETUP ▶ RECORD Menu

The Record Menu allows customization of continuous record setting. Click on [+] or [-] button to change these settings, and then click the 'SAVE' button to save and exit.

#### 6. BACKUP



To start the backup, right click on your mouse, then clickon the [Backup Menu].



The Backup menu allows copying of video from the recorder to a USB flash drive.

- 1. Select 'DEVICE', and choose 'USB'
- 2. Select the appropriate channel(s).
- 3. Set the start and end time range to copy the video.
- 4. Scroll down to 'ACTION' and click on [START] button to start the copying video.

NOTE: It is srtongly recommended that recording be stopped before performing a long-range BACKUP.

#### 7. LOGIN



Internet Explorer Login:

- - (For example: http:// 192.168.0.100:7000, http://G123456.dvrhost.com:7000)
- 2. Sign-in as either 'admin' or 'user'.
- 3. Enter the factory default password of 000000. (6 zero)
- 4. Click the 'OK' button.

Note: The HOSTNAME can be found under the 'INFO' tab in the "SYSTEM" menu of the DVR

# 8. MOBILE APP

The free "EVMobile" mobile app can be downloaded for Apple mobile devices in the App Store, or for the Android in Google Play. Download and install the EVMobile app before proceeding further.



Name: Type any name

IP:Port

hostname, dvrhost.com: 7000 Username: Type username Password: Type password

# 9. CAUTION

There is a risk of explosion if the battery is replaced with an incorrect type. Dispose of used batteries in accordance with local rules and regulation.

## 10. IMPORTANT NOTICE

This equipment is for indoor use only, and all the communication wiring is limited to the inside of the building.



